

Data sheet

SM 231 (231-1BD60)

Technical data

Order no.	231-1BD60
Туре	SM 231
General information	
Note	-
Features	4x AI 12 Bit Current 420 mA Potential separated per channel
Current consumption/power loss	
Current consumption from backplane bus	280 mA
Power loss	1.4 W
Technical data analog inputs	
Number of inputs	4
Cable length, shielded	200 m
Rated load voltage	-
Current consumption from load voltage L+ (without load)	-
Voltage inputs	-
Min. input resistance (voltage range)	-
Input voltage ranges	-
Operational limit of voltage ranges	-
Operational limit of voltage ranges with SFU	-
Basic error limit voltage ranges	-
Basic error limit voltage ranges with SFU	-
Destruction limit voltage	-
Current inputs	yes
Max. input resistance (current range)	20 Ohm
Input current ranges	+4 mA +20 mA
Operational limit of current ranges	-
Operational limit of current ranges with SFU	-
Grundfehlergrenze Strombereiche	-
Radical error limit current ranges with SFU	-
Destruction limit current inputs (electrical current)	max. 100mA
Destruction limit current inputs (voltage)	-
Resistance inputs	-
Resistance ranges	-
Operational limit of resistor ranges	-
Operational limit of resistor ranges with SFU	-
Basic error limit	-
Basic error limit with SFU	-
Destruction limit resistance inputs	-
Resistance thermometer inputs	-
Resistance thermometer ranges	-
Operational limit of resistance thermometer ranges	-
Operational limit of resistance thermometer ranges with SFU	-

YASKAWA

Basic error limit thermoresistor ranges - Basic error limit thermoresistor ranges with SFU - Thermocouple inputs - Thermocouple ranges - Operational limit of thermocouple ranges - Operational limit of thermocouple ranges with SFU - Basic error limit thermocouple ranges with SFU - Bestic error limit thermocouple ranges with SFU - Bestic error limit thermocouple ranges with SFU - Bestic error limit thermocouple ranges with SFU - Destruction limit thermocouple ranges with SFU - External temperature compensation - Internal temperature compensation - Temperature error internal compensation - Temperature error internal compensation 1 Resolution in bit 1 Massurement principle successive approximation Basic conversion time 1 Noise suppression for froquency 1		
Destruction limit resistance thermometer injusts - Thermocouple injusts - Thermocouple ranges - Operational limit of thermocouple ranges with SFU - Basic error limit thermocouple ranges with SFU - Intermable temperature compensation - Intermal temperature compensation - Temperature error internal compensation - Temperature error internal compensation 1 Temperature error internal compensation 1 Technical unit of temperature enasurement 1 Resolution in the 1 Basic conversion time 1 Basic conversion time 1 Basic conversion time 8	Basic error limit thermoresistor ranges	-
Thermocouple ranges - Operational limit of thermocouple ranges - Operational limit of thermocouple ranges with SFU - Basic error limit thermocouple ranges with SFU - Basic error limit thermocouple ranges with SFU - Programmable temperature compensation - External temperature compensation - Temperature error internal compensation - Temperature principle successive approximation Basic conversion tine - Rosolution in bit 12 Measurement principle successive approximation Basic conversion time - Noise suppression for frequency - Inlater and the properature error internal compensation - Status information, alarms, diagnostics Bye Status information properature nonon	Basic error limit thermoresistor ranges with SFU	-
Themscouple ranges	Destruction limit resistance thermometer inputs	-
Operational limit of thermocouple ranges - Operational limit of thermocouple ranges with SFU - Basic error limit thermocouple ranges with SFU - Destruction limit thermocouple ranges with SFU - Destruction limit thermocouple inputs - Programmable temperature compensation - External temperature compensation - Temperature error internal compensation - Basic conversion limit - Basic conversion time - Basic derror limit principle - Status information for error frequency - </td <td>Thermocouple inputs</td> <td>-</td>	Thermocouple inputs	-
Operational limit of thermocouple ranges - Basic error limit thermocouple ranges - Basic error limit thermocouple ranges with SFU - Programmable temperature compensation - External temperature compensation - Internal temperature compensation - Temperature error internal compensation - Temperature remeasurement - Resolution in bit 12 Measurement principle successive approximation Basic conversion time - Noise suppression for frequency - Initial data size 8 Byte Status information, alarms, diagnostics status information, alarms, diagnostics Status information, alarms, diagnostics - Status information, plants, diagnostics - Status information, alarms, diagnostic none Interrupts no Diagnostic information read-out no Diagnostic information read-out none Channel error display none Channel error display pone Channel error display pone<	Thermocouple ranges	-
Basic error limit thermocouple ranges - Basic error limit thermocouple inputs - Poestruction limit thermocouple inputs - External temperature compensation - External temperature compensation - Internal temperature compensation - Tomperature error internal compensation - Tombidal unit of temperature measurement - Resolution in bit 12 Measurement principle successive approximation Basic conversion time - Noise suppression for frequency - Initial data size 8 Byto Status information, alarms, diagnostics status information, alarms, diagnostics Status display none Process alarm no Diagnostic interrupt no Diagnostic functions no Diagnostic functions none Group error display none Channel error display pone Between channels of groups to 1 Between channels and backplane bus pes Between channels and powe	Operational limit of thermocouple ranges	-
Basic error limit thermocouple ranges with SPU - Destruction limit thermocouple inputs - Programmable temperature compensation - Internal temperature compensation - Temperature error internal compensation - Temperature error internal compensation - Technical unit of temperature measurement - Resolution in bit 12 Measurement principle successive approximation Basic conversion time - Noise suppression for frequency - Initial data size 8 Byte Status information, alarms, diagnostics status information, alarms, diagnostics Status display none Interrupts no Diagnostic interrupt no Diagnostic information read-out none Diagnostic information read-out none Supply vollage display none Group error display ps Between channels yes Between channels of groups to 1 Between channels and backplane bus yes Betwe	Operational limit of thermocouple ranges with SFU	-
Destruction limit thermocouple inputs - Programmable temperature compensation - External temperature compensation - Temperature error internal compensation - Temperature error internal compensation - Technical unit of temperature measurement - Resolution in bit 12 Measurement principle successive approximation Basic conversion time - Noise suppression for frequency - Initial data size 8 Byte Status information, alarms, diagnostics Status display Interrupts no Process alarm no Process alarm no Diagnostic interrupt no Diagnostic information read-out none Supply voltage display none Group error display none Channel error display none Channel error display ge Between channels of groups to 1 Between channels of groups to 1 Between channels and backplane bus ges <	Basic error limit thermocouple ranges	-
Programmable temperature compensation - External temperature compensation - Internal temperature error internal compensation - Temperature error internal compensation - Temperature error internal compensation - Resolution in bit 12 Measurement principle successive approximation Basic conversion time - Noise suppression for frequency - Initial data size 8 Byte Status information, alarms, diagnostics Status information, alarms, diagnostics Status display none Interrupts no Poccess alarm no Diagnostic functions no Diagnostic functions no Diagnostic information read-out none Supply voltage display none Group error display none Channel error display pone Between channels yes Between channels of groups to 1 Between channels of groups to 1 Between channels and backplane bus yes	Basic error limit thermocouple ranges with SFU	-
External temperature compensation - Internal temperature compensation - Temperature error internal compensation - Temperature error internal compensation - Technical unit of temperature measurement - Resolution in bit 12 Measurement principle successive approximation Basic conversion time - Noise suppression for frequency - Initial data size 8 Byte Status information, alarms, diagnostics - Status display none Interrupts no Process alarm no Diagnostic functions no Diagnostic functions no Diagnostic functions no Supply voltage display none Group error display none Group error display red LED per channel Between channels yes Between channels of groups to 1 Between channels and backplane bus yes Between channels and power supply yes Max. potenti	Destruction limit thermocouple inputs	-
Internal temperature compensation -	Programmable temperature compensation	-
Temperature error internal compensation - Technical unit of temperature measurement - Resolution in bit 12 Measurement principle successive approximation Basic conversion time - Noise suppression for frequency - Initial data size 8 Byte Status information, alarms, diagnostics Status display none Interrupts no Process alarm no Diagnostic functions no Diagnostic functions no Diagnostic functions no Supply voltage display none Group error display none Group error display none Between channels yes Between channels of groups to 1 Between channels and backplane bus yes Between channels and power supply yes Max. potential difference between inputs (urn) DC 75 V/ AC 50 V Max. potential difference between Mana and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between Inputs and Mana (Ucm)	External temperature compensation	-
Technical unit of temperature measurement - Resolution in bit 12 Measurement principle successive approximation Basic conversion frime - Noise suppression for frequency - Initial data size 8 Byte Status information, alarms, diagnostics Status display none Interrupts no Process alarm no Diagnostic interrupt no Diagnostic interrupt no Diagnostics information read-out none Supply voltage display none Group error display none Channel error display none Estween channels yes Between channels of groups to 1 Between channels of groups to 1 Between channels and backplane bus yes Between channels and power supply yes Max. potential difference between inputs (Ucm) DC 75 V/ AC 50 V Max. potential difference between Inputs and Mana (Ucm) C 75 V/ AC 50 V Max. potential difference between Inputs and Mintern (Uiso	Internal temperature compensation	-
Resolution in bit Measurement principle Successive approximation Basic conversion time - Noise suppression for frequency - Initial data size 8 Byte Status information, alarms, diagnostics Status information, alarms, diagnostics Status display none Interrupts no Process alarm no Diagnostic interrupt no Diagnostic interrupt no Diagnostic interrupt none Diagnostic interrupt none Channel error display red LED per channel Supply voltage display forup error display red LED per channel Between channels of groups to 1 Between channels and power supply wes Between channels and power supply wax. potential difference between inputs (Ucm) Max. potential difference between inputs and Mana (Ucm) Max. potential difference between inputs and Mana (Ucm) Max. potential difference between inputs and Mana (Ucm) Max. potential difference between Mana and Mintern (Uiso) Max. potential difference between inputs and Mana (Ucm) Max. potential difference between Mana and Mintern (Uiso) Max. potential difference between Mintern and outputs - Constitution De C 75 V/ AC 50 V Max. potential difference between Mintern and outputs - Constitution De C 75 V/ AC 50 V Max. potential difference between Mintern and outputs - Constitution De C 75 V/ AC 50 V Max. potential difference between Mintern and outputs - Constitution De C 75 V/ AC 50 V Max. potential difference between Mintern and outputs - Constitution De C 75 V/ AC 50 V Max. potential difference between Mintern and outputs -	Temperature error internal compensation	-
Measurement principle successive approximation Basic conversion time Noise suppression for frequency Initial data size 8 Byte Status display none Interrupts no - Process alarm no - Diagnostic interrupt no - Diagnostic functions none Diagnostic functions none Channel error display none Channel error display red LED per channel Between channels of groups to 1 Between channels and backplane bus yes Between channels and power supply yes Between channels and power supply yes Between channels and power supply yes Max. potential difference between inputs (Ucm) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) - C 50 V Max. potential difference between Mana and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) - C 50 V Max. potential difference between Mana and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between Mana and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between Mana and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between Mana and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between Mana and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between Mana and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between Mana and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between Mana and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between Mintern and outputs - C 50 V Max. potential difference between Mintern and outputs - C 50 V Datastizes Upput bytes 8 Output bytes 0 Parameter bytes 0 Dagnostic bytes 0 Dagnostic bytes 0	Technical unit of temperature measurement	-
Basic conversion time - Noise suppression for frequency - Initial data size 8 Byte Status information, alarms, diagnostics Status display none Interrupts no Process alarm no Diagnostic interrupt no Diagnostic functions no Diagnostics information read-out none Supply voltage display none Group error display none Channel error display red LED per channel Isolation Between channels of groups to 1 Between channels and backplane bus yes Between channels and power supply yes Max. potential difference between circuits DC 75 V/ AC 50 V Max. potential difference between inputs (Ucm) DC 75 V/ AC 50 V Max. potential difference between Inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between Inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between Inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between Inpu	Resolution in bit	12
Noise suppression for frequency - Initial data size 8 Byte Status information, alarms, diagnostics Status display none Interrupts no Process alarm no Diagnostic interrupt no Diagnostic functions no Diagnostic information read-out none Supply voltage display none Channel error display red LED per channel Isolation yes Between channels yes Between channels of groups to 1 Between channels and backplane bus yes Between channels and power supply yes Max. potential difference between injust (Ucm) DC 75 V/ AC 50 V Max. potential difference between injust and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between injust and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between injust and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between injust and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between injust and Mintern (Uiso) DC 500 V <	Measurement principle	successive approximation
Initial data size 8 Byte Status information, alarms, diagnostics Status display none Interrupts no Process alarm no Diagnostic interrupt no Diagnostic interrupt no Diagnostic interrupt no Diagnostic interrupt none Diagnostic information read-out none Supply voltage display none Channel error display red LED per channel Stoption Steween channels yes Between channels yes Between channels of groups to 1 Between channels nd backplane bus yes Between channels and power supply yes Max. potential difference between inputs (Ucm) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) Amax. potential difference between inputs and Mana (Ucm) Amax. potential difference between inputs and Mana (Ucm) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) DC 75 V/ AC 50	Basic conversion time	-
Status information, alarms, diagnostics Status display none Interrupts no Process alarm no Diagnostic interrupt no Diagnostic functions no Diagnostic functions none Supply voltage display none Group error display none Channel error display red LED per channel Isolation Between channels of groups to 1 Between channels and backplane bus yes Between channels and power supply yes Between channels and power supply yes Between channels and power supply possible inference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) Amx. potential difference between inputs and Mana (Ucm) Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between Mintern and outputs - Insulation tested with DC 500 V	Noise suppression for frequency	-
Status display Interrupts Interrupts Interrupts Interrupt Interrup	Initial data size	8 Byte
Interrupts no no Process alarm no no Diagnostic interrupt no no Diagnostic interrupt no no Diagnostic functions no none Diagnostic functions none Diagnostic sinformation read-out none Supply voltage display none Channel error display none red LED per channel stouch sold process of groups to 1 Diagnostic groups to 1 Diagnostic groups to 1 Diagnostic and power supply yes Detween channels and backplane bus yes Detween channels and power supply yes Max. potential difference between inputs and Mana (Ucm) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) DC 75 V/ AC 50 V Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) DC 75 V/ AC 50 V Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between Mintern and outputs DC 75 V/ AC 50 V Max. potential difference between Mintern and outputs DC 75 V/ AC 50 V Max. potential difference between Mintern and outputs DC 75 V/ AC 50 V Max. potential difference between Mintern and outputs DC 75 V/ AC 50 V Max. potential difference between Mintern and outputs DC 75 V/ AC 50 V Max. potential difference between Mintern and outputs DC 75 V/ AC 50 V Max. potential difference between Mintern and outputs DC 75 V/ AC 50 V Max. potential difference between Mintern and outputs DC 75 V/ AC 50 V Max. potential difference between Mintern and outputs DC 75 V/ AC 50 V Max. potential difference between Mintern Mi	Status information, alarms, diagnostics	
Process alarm no no Diagnostic interrupt no no Diagnostic interrupt none Diagnostic functions none Diagnostics information read-out none Supply voltage display none Group error display none Parameter bytes of Sanasan Sanas	Status display	none
Diagnostic interrupt none Diagnostic functions none Diagnostics information read-out none Supply voltage display none Group error display none Channel error display red LED per channel Isolation Between channels Between channels of groups to 1 1 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2	Interrupts	no
Diagnostic functions none Diagnostics information read-out none Supply voltage display none Group error display none Channel error display red LED per channel Isolation Between channels yes Between channels of groups to 1 Between channels and backplane bus yes Between channels and power supply yes Max. potential difference between circuits DC 75 V/ AC 50 V Max. potential difference between inputs (Ucm) DC 75 V/ AC 50 V Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) - CNAMAX. potential difference between inputs and Mana (Ucm) - CNAMAX. potential difference between inputs and Mana (Ucm) - CNAMAX. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between Mana and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) - CNAMAX. potential difference between Mintern and outputs - CNAMAX. potential difference b	Process alarm	no
Diagnostics information read-out none Supply voltage display none Group error display none Channel error display red LED per channel Isolation Between channels Between channels of groups to 1 Between channels and backplane bus yes Between channels and power supply yes Max. potential difference between inputs (Ucm) DC 75 V/ AC 50 V Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between Mintern and outputs - Insulation tested with DC 500 V Datasizes Input bytes 8 Output bytes 0 Parameter bytes 3 Diagnostic bytes	Diagnostic interrupt	no
Supply voltage display none Group error display none Channel error display red LED per channel Isolation Between channels Between channels of groups to 1 Between channels and backplane bus yes Between channels and power supply yes Max. potential difference between circuits DC 75 V/ AC 50 V Max. potential difference between mputs (Ucm) DC 75 V/ AC 50 V Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between Mintern and outputs - Insulation tested with DC 500 V Datasizes Input bytes 8 Output bytes 0 Parameter bytes 3 Diagnostic bytes	Diagnostic functions	no
Group error display red LED per channel Isolation Between channels yes Between channels of groups to 1 Between channels and backplane bus yes Between channels and power supply yes Max. potential difference between circuits DC 75 V/ AC 50 V Max. potential difference between inputs (Ucm) DC 75 V/ AC 50 V Max. potential difference between Mana and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) - Max. potential difference between inputs and Mana (Ucm) - Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between Mintern and outputs - Insulation tested with DC 500 V Datasizes Input bytes Output bytes	Diagnostics information read-out	none
Isolation Between channels yes Between channels of groups to 1 Between channels and backplane bus yes Between channels and power supply yes Max. potential difference between circuits DC 75 V/ AC 50 V Max. potential difference between inputs (Ucm) DC 75 V/ AC 50 V Max. potential difference between Mana and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) - Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between Mintern and outputs - Insulation tested with DC 500 V Datasizes Input bytes 8 Output bytes 0 Parameter bytes 3 Diagnostic bytes 0	Supply voltage display	none
Between channels yes Between channels of groups to 1 Between channels and backplane bus yes Between channels and power supply yes Max. potential difference between circuits DC 75 V/ AC 50 V Max. potential difference between inputs (Ucm) DC 75 V/ AC 50 V Max. potential difference between Mana and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) - Max. potential difference between inputs and Mana (Ucm) - Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between Mintern and outputs - Insulation tested with DC 500 V Datasizes Input bytes 8 Output bytes 8 Output bytes 0 Parameter bytes 3 Diagnostic bytes 0	Group error display	none
Between channels of groups to 1 Between channels and backplane bus yes Between channels and power supply yes Max. potential difference between circuits DC 75 V/ AC 50 V Max. potential difference between inputs (Ucm) DC 75 V/ AC 50 V Max. potential difference between Mana and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) - Max. potential difference between inputs and Mana (Ucm) - Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between Mintern and outputs - Insulation tested with DC 500 V Datasizes Input bytes B COutput bytes O Upput bytes O G Parameter bytes O G O G O G O G O G O G O G O	Channel error display	red LED per channel
Between channels of groups to Between channels and backplane bus Between channels and power supply yes Max. potential difference between circuits DC 75 V/ AC 50 V Max. potential difference between inputs (Ucm) DC 75 V/ AC 50 V Max. potential difference between Mana and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) Amax. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between Mintern and outputs - Insulation tested with DC 500 V Datasizes Input bytes 8 Output bytes 0 Parameter bytes 3 Diagnostic bytes	Isolation	
Between channels of groups to Between channels and backplane bus Between channels and power supply yes Max. potential difference between circuits DC 75 V/ AC 50 V Max. potential difference between inputs (Ucm) DC 75 V/ AC 50 V Max. potential difference between Mana and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mana (Ucm) Ax. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between Mintern and outputs - Insulation tested with DC 500 V Datasizes Input bytes 8 Output bytes 0 Parameter bytes 3 Diagnostic bytes	Between channels	yes
Between channels and power supply Max. potential difference between circuits DC 75 V/ AC 50 V Max. potential difference between inputs (Ucm) DC 75 V/ AC 50 V Max. potential difference between Mana and Mintern (Uiso) Max. potential difference between inputs and Mana (Ucm) Max. potential difference between inputs and Mana (Ucm) Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between Mintern and outputs - Insulation tested with DC 500 V Datasizes Input bytes 8 Output bytes 0 Parameter bytes 3 Diagnostic bytes 0	Between channels of groups to	1
Between channels and power supply Max. potential difference between circuits Max. potential difference between inputs (Ucm) Max. potential difference between Mana and Mintern (Uiso) Max. potential difference between Mana and Mintern (Uiso) Max. potential difference between inputs and Mana (Ucm) Max. potential difference between inputs and Mintern (Uiso) Max. potential difference between inputs and Mintern (Uiso) Max. potential difference between Mintern and outputs - Insulation tested with DC 500 V Datasizes Unput bytes 8 Output bytes 0 Parameter bytes 3 Diagnostic bytes 0	Between channels and backplane bus	ves
Max. potential difference between circuits Max. potential difference between inputs (Ucm) DC 75 V/ AC 50 V Max. potential difference between Mana and Mintern (Uiso) Max. potential difference between inputs and Mana (Ucm) Max. potential difference between inputs and Mana (Ucm) Max. potential difference between inputs and Mintern (Uiso) DC 75 V/ AC 50 V Max. potential difference between Mintern and outputs Insulation tested with DC 500 V Datasizes Input bytes 8 Output bytes 0 Parameter bytes 3 Diagnostic bytes	Between channels and power supply	
Max. potential difference between inputs (Ucm) Max. potential difference between Mana and Mintern (Uiso) Max. potential difference between inputs and Mana (Ucm) Max. potential difference between inputs and Mintern (Uiso) Max. potential difference between inputs and Mintern (Uiso) Max. potential difference between Mintern and outputs Insulation tested with DC 500 V Datasizes Input bytes 8 Output bytes 0 Parameter bytes 3 Diagnostic bytes OC 75 V/ AC 50 V 0 OC 75 V 0 O		
Max. potential difference between inputs and Mana (Ucm) Max. potential difference between inputs and Mintern (Uiso) Max. potential difference between Mintern and outputs Insulation tested with DC 500 V Datasizes Input bytes 8 Output bytes 0 Parameter bytes Diagnostic bytes OUTPUT DIAGRAPHICAL STATEMENT OF THE PROPERTY OF		DC 75 V/ AC 50 V
Max. potential difference between inputs and Mintern (Uiso) Max. potential difference between Mintern and outputs Insulation tested with DC 500 V Datasizes Input bytes 8 Output bytes 0 Parameter bytes Diagnostic bytes OUTPUT DIAGRAPHICAL STATE OF THE PROPERTY	Max. potential difference between Mana and Mintern (Uiso)	DC 75 V/ AC 50 V
Max. potential difference between inputs and Mintern (Uiso) Max. potential difference between Mintern and outputs Insulation tested with DC 500 V Datasizes Input bytes 8 Output bytes 0 Parameter bytes Diagnostic bytes OUTPUT DIAGRAPHICAL STATE OF THE PROPERTY		-
Max. potential difference between Mintern and outputs Insulation tested with DC 500 V Datasizes Input bytes 8 Output bytes 0 Parameter bytes Diagnostic bytes 0		DC 75 V/ AC 50 V
Insulation tested withDC 500 VDatasizesInput bytes8Output bytes0Parameter bytes3Diagnostic bytes0		-
DatasizesInput bytes8Output bytes0Parameter bytes3Diagnostic bytes0	· · · · · · · · · · · · · · · · · · ·	DC 500 V
Input bytes 8 Output bytes 0 Parameter bytes 3 Diagnostic bytes 0	Datasizes	
Output bytes 0 Parameter bytes 3 Diagnostic bytes 0		8
Parameter bytes 3 Diagnostic bytes 0		
Diagnostic bytes 0		
	•	
	Housing	



Material	PPE / PA 6.6
Mounting	Profile rail 35 mm
Mechanical data	
Dimensions (WxHxD)	25.4 mm x 76 mm x 88 mm
Net weight	90 g
Weight including accessories	-
Gross weight	-
Environmental conditions	
Operating temperature	0 °C to 60 °C
Storage temperature	-25 °C to 70 °C
Certifications	
UL certification	yes
KC certification	-